

Express Mail Label No.: EL751290694US

PATENT APPLICATION
Docket No.: 2807.2.22.6

UNITED STATES PATENT APPLICATION

of

Michael H. Myers

John N. Hait

and

Steven F. McDaniel

for

PHOTONIC WAVELENGTH ERROR DETECTOR

BACKGROUND

1. The Field of the Invention

This invention relates to computer systems, telecommunication networks, and switches therefor and, more particularly, to novel systems and methods for switching and processing photonic information.

2. Background Discussion

Multiplexing is a method for transmitting multiple, distinct signals over a single physical carrier medium. Much of the protocol of computer hardware deals with the encoding and decoding of signals according to some time scheme for maintaining signal integrity and uniqueness from other signals. In conventional time-division types of multiplexing, signals are transmitted within specific time slots or burst positions. In order to prevent individual bits from being transmitted at the same time, each burst of bits may be encoded into a signal and transmitted over the carrier medium at a specific time.

As transmission rates increase, the individual time divisions available for each small quantity of information in a signal are reduced. However, with the advent of photonic processing, the transmission, encoding, and decoding of photonic signals taken from the electromagnetic spectrum, deserve further consideration. In conventional computer systems, as well as conventional telecommunications networks, the switching, routing, and transmission of signals throughout networks and between processors or processes may be a major limiting factor in performance. Typically, transmissions of a signal require encoding of the signal in a carrier medium, according to a protocol or format.

Thereafter, transmission occurs as a physical phenomenon in which light, or other electromagnetic radiation, electrical signals, mechanical transmissions, or the like are transferred between a source and a destination. At the destination, a decoder must then manipulate the physical response to the incoming signals, thus reconstructing original data encoded by the sender. Communications in general may include communications between individual machines. Machines may be network-aware, hardware of any variety, individual computers, individual components within computers, and the like.

Thus, the issue of sending and receiving information or message traffic is of major consequence in virtually all aspects of industrial and commercial equipment and devices in the information age. Whether communications involve sending and receiving information between machines, or telecommunications of data signals, audio signals, voice, or the like over conventional telecommunications networks, the sending and receiving requirements of rapidly encoding and decoding are present.

With the advent of photonic signals and photonic signal processing, new speed limits are being approached by transmission media. Moreover, origination of signals can now be executed literally at light speeds. Accordingly, what is needed is a system for multiplexing photonic signals over photonic carrier media in such a way as to maximize speed, while maintaining the integrity of information.

To be most useful, communications and switching equipment must interface with data channels from a plethora of sources. An ability to transmit and redirect multiple channels simultaneously and independently, increases the capacity and usefulness of transmission, multiplexing and switching equipment. Over the years several standard methods have been

developed for packing multiple channels onto a single transmission medium. In optical frequency division multiplexing (OFDM) and wavelength division multiplexing (WDM), each channel has a unique wavelength which typically remains constant with time. In spread spectrum systems, all channels may have substantially the same average wavelength with short term variations that are unique to each channel. Typically, sets of orthogonal functions are used to define channel wavelengths. In most systems and applications, it may be desirable that the wavelength of each channel can be described as a function of time, distinct and unique from all other channels. An ability to wavelength shift photonic signals from one channel, whose wavelength can be defined as a function of time, into any other channel would facilitate the transmission, multiplexing and switching of an extremely wide range of photonic signals.

One dilemma in engineering photonic systems is the conversion of signals or information between the electronic and photonic domains. Photonic systems are capable of high transmission rates and distances. Computers and control equipment are typically electronic due to their flexibility, low cost and wide availability. Typically, switching and multiplexing require the conversion of optical signals into electrical signals for processing and control, followed by reconversion into the optical domain for further transmission. An ability to direct and control a photonic stream of data with electronic devices and systems without requiring conversion of the photonic data stream to the electronic domain would leverage the best characteristics of each domain.

While it may be desirable to leave data in the photonic domain when transmitting, multiplexing and switching photonic signals, it is often desirable to encode an electronic data signal onto an existing carrier without additional complexity and cost. An ability to process

photonic or electronic data signals with the same mechanism would simplify interfacing with a wide range of communications, process control, and computational equipment.

One difficulty in interfacing a wide variety of photonic equipment is the assignment of channel wavelengths and encoding techniques. Setup and configuration become problematic. An ability to automatically channelize (change the wavelength of a photonic carrier to a given channel) and transparently pass along a data encoded photonic stream across a network of photonic equipment without prior knowledge of the channel wavelengths and encoding techniques would reduce the cost and complexity of deploying photonic equipment.

Another issue in photonic transmission systems is carrier wavelength variability due to component variability, temperature drift, system jitter and other factors. Carrier wavelength variability makes it difficult to densely pack channels onto a transmission medium without collisions occurring, especially when multiplexing channels from multiple sources. Typically, expensive, temperature-compensated, reference lasers or light sources are required to stabilize a photonic signal. Most state-of-the-art photonic transmission systems require conversion to the electronic domain followed by remodulation of a light source and retransmission in order to eliminate any jitter introduced during transmission. An ability to compensate for wavelength variability of existing photonic streams without remodulation and retransmission would increase the capacity and lower the cost of transmission, multiplexing and switching equipment.

BRIEF SUMMARY AND OBJECTS OF THE INVENTION

In view of the foregoing, it is a primary objective of the present invention to provide a method and apparatus for transmitting, multiplexing and switching photonic signals without

requiring conversion to the electronic domain. It is also a primary objective of the present invention to provide a method and apparatus for embedding electronic data signals onto existing photonic carriers and signals.

One objective of the invention is to provide a system that facilitates the transmission, multiplexing and switching of an extremely wide range of photonic signals. It is also an objective of the invention to provide a system for multiplexing photonic signals over photonic carrier media in such a way as to maximize speed, while maintaining the integrity of information. Another objective of the invention is the ability to interface with data channels from a plethora of sources, to transmit and redirect those data channels simultaneously and independently. In particular it is desired to wavelength shift photonic signals from one channel, whose wavelength can be defined as a function of time, into any other channel without requiring conversion to and reconversion from the electronic domain. It is also an objective of the invention to automatically channelize and transparently pass along a data encoded photonic stream across a network of photonic equipment without prior knowledge of the channel wavelengths or encoding methods and to compensate for wavelength variability of existing photonic streams without retransmission.

The present invention uses various embodiments to wavelength shift photonic signals. Wavelength shifting is also applied as a mechanism to multiplex, switching and transmit photonic signals. In certain embodiments in accordance with the invention, an apparatus for wavelength shifting uses modulation techniques to change photonic carrier wavelengths. Modulation techniques may be selected to be appropriate to a modulation device of choice. A

particular modulation device may be driven by a modulation synthesizer producing a controlling waveform optimized for the device.

Consistent with the foregoing objectives, and in accordance with the invention as embodied and broadly described herein, an apparatus and method are disclosed, in suitable detail to enable one of ordinary skill in the art to make and use the invention.

BRIEF DESCRIPTION OF THE DRAWINGS

The foregoing and other objectives and features of the present invention will become more fully apparent from the following description and appended claims, taken in conjunction with the accompanying drawings. Understanding that these drawings depict only typical embodiments of the invention and are, therefore, not to be considered limiting of its scope, the invention will be described with additional specificity and detail through use of the accompanying drawings in which:

Figure 1 is a schematic block diagram of a wavelength shifting apparatus in accordance with the invention;

Figure 2 is a schematic diagram of a quadrature Mach-Zehnder modulation device used in accordance with the invention;

Figure 3 is a graph of the Mach-Zehnder device transfer function in accordance with the device of Figure 2;

Figure 4 is a schematic block diagram of a modulation synthesizer used in accordance with the invention;

Figure 5 is a schematic block diagram of an embodiment of a modulation synthesizer configured to perform ON/OFF keying in accordance with the invention;

Figure 6 is a schematic diagram of a phase modulation device used in accordance with the invention;

5 Figure 7 is a schematic block diagram of an embodiment of a modulation synthesizer configured to perform frequency shift keying in accordance with the invention;

Figure 8 is a schematic block diagram of a wavelength error detector in accordance with the invention;

Figure 9 is a schematic block diagram of a tunable wavelength error detector in accordance with the invention;

10 Figure 10 is a schematic block diagram of a tunable wavelength error detector in accordance with the invention; and

Figure 11 is a schematic block diagram of a channel allocation mechanism in accordance with the invention;

15 Figure 12 is a schematic block diagram of a tunable wavelength stabilized transmitter in accordance with the invention;

Figure 13 is a schematic block diagram of a recursive wavelength shifter in accordance with the invention; and

20 Figure 14 is a set of frequency domain graphs of several signals associated with one embodiment of the recursive wavelength shifter depicted in Figure 13.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

It will be readily understood that the components of the present invention, as generally described and illustrated in the Figures herein, may be arranged and designed in a wide variety of different configurations. Thus, the following more detailed description of the embodiments of the system and method of the present invention, as represented in Figures 1 through 14, is not intended to limit the scope of the invention. The scope of the invention is as broad as claimed herein. The illustrations are merely representative of certain, presently preferred embodiments of the invention. Those presently preferred embodiments of the invention will be best understood by reference to the drawings, wherein like parts are designated by like numerals throughout.

Those of ordinary skill in the art will, of course, appreciate that various modifications to the details of the Figures may easily be made without departing from the essential characteristics of the invention. Thus, the following description of the Figures is intended only by way of example, and simply illustrates certain example embodiments consistent with the invention as claimed.

The design, implementation and deployment of photonic systems involves the convergence of a number of disciplines each with their own working vocabularies. Additionally, the novelty of the present invention presents some new terms and concepts. The following definitions therefore are provided for the readers convenience:

Channel: A virtual medium for signal propagation. Channels allow a single medium to carry multiple signals simultaneously.

Channel Spacing: The distance between channels usually expressed in cycles per second.

Wavelength Shifting: The act of changing the wavelength of a photonic signal, particularly the carrier.

Wavelength Variability: A measure of wavelength deviation from an ideal or desired wavelength over a given period of time.

5 Wavelength Stabilization: The act of reducing wavelength variability.

Wavelength Pattern: The pattern (over time) followed by the wavelength of a photonic signal, particularly the carrier. May be a constant. The present invention associates wavelength patterns with channels.

Channelization: The act of shifting the wavelength of a photonic signal to match the wavelength pattern of a given channel.

Wavelength Signature: An information set that captures the essential elements of the wavelength of a photonic signal such as the pattern, signal jitter, variance etc.

Orthogonal Signals: Signals that do not correlate over a given period of time. Selecting wavelength patterns that are orthogonal helps minimize interference between channels.

15 Wavelength Division Multiplexing: Combining multiple signals onto a medium where each signal has a different wavelength.

Spread Spectrum Channels: Channels with wavelength patterns that are very dynamic. Usually based on orthogonal functions.

20 Spreading Function: Essentially a wavelength pattern used to change fixed wavelength channels to spread spectrum channels.

Gathering Function: Essentially a wavelength pattern used to change spread spectrum channels to fixed wavelength channels.

Modulation: The act of varying a frequency, amplitude, phase or similar characteristic of a signal.

Modulation Waveform: A waveform used to modulate a signal and thereby vary the frequency, amplitude, phase or similar characteristic of a signal. The present invention uses a modulation waveform to drive (i.e. control) a modulation device.

Modulation Synthesizer: A method or apparatus that generates a modulation waveform in response to various control parameters or signals.

Pre-modulation: Modulation of the modulation waveform. The modulation synthesizer of the present invention uses pre-modulation to encode data simultaneous with wavelength shifting.

In optical and photonic systems it is usually more convenient to refer to carriers in terms of wavelength rather than frequency. Despite this preference, channel spacing is usually expressed in frequency units rather than units of length. Throughout this description it is implied that the amount of shifting is expressed in terms of frequency (Hz) while the result (a change in carrier wavelength) is referred to as wavelength shifting.

Referring to Figure 1 specifically, while generally referring to all the Figures, a wavelength shifter 10 with stabilization and data encoding may include a modulation synthesizer 12, a wavelength error detector 14, and a modulation device 16. The modulation device 16 may receive a photonic signal 18 and provide a channelized photonic signal 20 wherein the wavelength follows a signature or pattern associated with a channel.

The modulation device 16 may receive a photonic signal 18 that may be composite or non-composite. Composite signals may contain a plurality of wavelengths, each wavelength

definable as a function of time, while non-composite signals have a single wavelength also definable as a function of time. Regardless of the complexity of the photonic signal 18, the modulation device 16 receives the photonic signal 18 and may provide a channelized photonic signal 20 wherein each wavelength follows a pattern corresponding to a particular channel.

5 In most embodiments, the modulation device 16 may be a full-duplex device capable of simultaneously modulating signals from both directions. With a full-duplex modulation device 16, the wavelength shifter 10 may be also full-duplex. In full-duplex operation the modulation device 16 receives the photonic signal 18 and provides the channelized photonic signals 20 in each direction. For simplicity, this description is restricted to half-duplex operation unless otherwise noted.

10 Under proper control, the wavelength shifter 10 may direct a non-composite photonic input into any one of an arbitrary number of output channels. Composite signals may be similarly directed. For example, a composite signal comprised of multiple wavelengths that are equally spaced by a fixed frequency interval, may be shifted up or down as a group by an arbitrary frequency to occupy a new set of wavelengths. The wavelength shifter 10 may be designed to stabilize and channelize the photonic signal 18. Typically, the channelized photonic signal 20 will have the same complexity as the photonic signal 18 and will be a composite signal if the photonic signal 18 is a composite signal. The channelized photonic signal 20 differs from the photonic signal 18 in that the wavelengths of the photonic signal 18 may be shifted to match a wavelength pattern associated with a channel. In some embodiments, the photonic signal 18 may also have a wavelength pattern but it is generally assumed that the wavelength patterns are externally originated and may be unknown to the system of interest.

The modulation synthesizer 12 may receive an optional data signal 22 and a shift signal 24. The modulation synthesizer may provide a modulation waveform 26 designed to channelize the photonic signal 18 via the modulation device 16. The optional data signal 22 may be used to pre-modulate the modulation waveform 26 and effectively encode data in the channelized photonic signal 20. Pre-modulation allows data encoding techniques such as Frequency Shift Keying, ON/OFF keying, and code division keying to be performed by the wavelength shifting modulation device.

Time-domain orthogonal codes may be directly used by the modulation synthesizer 12 when pre-modulating the modulation waveform. Frequency-domain orthogonal codes such as frequency shift keying Walsh codes may be converted to a time-domain waveform and used to pre-modulate the modulation waveform. Joint time-frequency codes may also be used. For example, one bits may be encoded by a positive frequency shift in an alternating ON-OFF pattern while zero bits may be encoded by a negative frequency shift in an alternating OFF-ON pattern.

The ability to simultaneously encode data, channelize and stabilize a photonic signal via a single modulation device has not been found in the art and appears to be unique to the wavelength shifter 10. In some embodiments, the optional data signal 22 is not used and the modulation synthesizer 12 may simply be a voltage-controlled quadrature oscillator.

The wavelength error detector 14 may monitor the channelized photonic signal 20 and provide a wavelength error signal 21 useful for correcting errors in wavelength. The wavelength error detector 14 may monitor a single channel or a representative channel of a group of active channels. While certain embodiments cannot independently shift and correct wavelength errors in separate channels (using a single wavelength shifter 10), wavelength errors may be minimized

across multiple active channels (using a single wavelength shifter 10) by generating a wavelength error signal that is the weighted average of the wavelength error of each channel. Typically, if a group of channels is derived from the same laser or light source, selecting a representative channel may be just as effective and much less costly than generating an averaged wavelength error signal.

The wavelength shifter 10 allows stabilization of a single channel or group of channels without requiring direct control of a laser or light source. Separating stabilization from the actual laser device allows for greater flexibility in designing and deploying photonic systems.

Separating the wavelength error detector 14 from the synthesis and modulation functions of the wavelength shifter 10 also allows for system design flexibility. Depending on the application, the wavelength error detector 14 may operate about a wavelength that is fixed or tunable. The wavelength error detector 14 may be dedicated to a single wavelength shifter or shared among multiple wavelength shifters 10. The wavelength error detector 14 may also be dynamic and support wavelength signatures or patterns. Regardless of the application, the wavelength error signal 21 provides feedback to the modulation synthesizer 12 which may effect shifting, stabilization and channelization of the photonic signal 18.

Certain embodiments in accordance with the present invention use a modulation device to shift and stabilize the wavelength of a carrier. Data encoding may also be performed with the wavelength shifter 10 via an optional data signal 22. A shift signal 24 controls the extent by which a wavelength may be shifted by the wavelength shifter 10 (neglecting any wavelength error correction). The shift signal 24 may have a constant value or the shift signal 24 may be a dynamic signal with a spreading or gathering function.

Separating the shift signal 24 from the wavelength error signal 21 allows for greater control and flexibility of the wavelength shifter 10. Wavelength shifting of the photonic signal 18 may advantageously occur through either mechanism. For example, the shift signal 24 may correspond to a wavelength pattern, while the wavelength error signal 21 may provide fine tuning of the average wavelength of the channelized photonic signal 20. In the embodiments depicted in Figures 1-11, the shift signal 24 and the wavelength error signal 21 are equal and independent in their ability to effect a wavelength shift on the photonic signal 18 and thereby provide the channelized photonic signal 20.

The wavelength shifter 10 may be used to interface between systems with dissimilar channel wavelength patterns. For example, one system may use spread spectrum channels while another may use channels with fixed wavelengths. By providing a spreading function or conversely an unspreading function to the shift signal 24, the wavelength shifter 10 may be used to convert fixed wavelength channels to spread spectrum channels and vice versa. Conversion between two spread spectrum channels may occur by providing the difference of two spreading functions to the shift signal 24.

In certain embodiments, the shift signal 24 controls the amount of shift in units of frequency (Hz). In some embodiments, the shift signal 24 provides a shift range, allowing wavelength error correction to occur within that range. Specifying a shift range on the shift signal 24, allows the wavelength shifter 10 to lock onto a particular channel when wavelength shifting a composite photonic signal. Wavelength shifting a composite photonic signal without a shift range may result in channel wandering should a composite signal experience fading or some other kind of degradation.

The shift signal 24 may be data keyed instead of using the optional data signal 22. Data keying with the shift signal 24 effectively creates spread spectrum or frequency domain data keying. Frequency shift keying is perhaps the simplest form of frequency domain data keying wherein the shift signal 24 alternates between two shift values to encode the data. The shift signal 24 may be data keyed with binary codes such as Walsh codes. Continuous codes may also be used.

One operation, that may be used for processing signals and creating filters, is a delay and sum operation. By controlling the relative phase of summed signals various degrees of constructive and destructive interference may be accomplished at a particular wavelength or frequency. By splitting photonic waves into multiple paths of various delays and recombining the split waves onto a single path, filters of various types can be created.

One element used in accordance with the invention is a phase modulator. Phase modulators often vary the index of refraction of a particular section of a waveguide and may be controlled with an applied voltage. Changing the index of refraction effectively changes the propagation time or delay through a medium. The ability to dynamically control the delay of a path via an applied voltage adds additional power for processing photonic signals.

For example, a Mach-Zehnder modulator may split a photonic signal onto two complementary pathways of identical length each with a phase modulator. With no applied voltage, the split photonic signals arrive in phase and effectively sum to the original photonic signal. Symmetrically increasing the delay of one path and decreasing the delay of the other path (via the applied voltages) allows the amplitude of the combined photonic signal to be modulated.

At a certain point the combined signals will be 180 degrees out of phase resulting in a zero amplitude signal known as a dark point.

Normally, amplitude modulation produces dual side bands resulting in wasted bandwidth. Quadrature modulation involves using two modulators that operate 90 degrees out of phase. Each modulator produces dual sidebands. Two of the sidebands cancel while two of the sidebands sum to create a single sideband.

Various modulation devices may be suitable for the modulation device 16. Suitable devices may include a quadrature Mach-Zehnder modulation device 16a, a phase modulation device 16b and a single Mach-Zehnder modulation device in concert with a phase modulator. Other possibilities include a single Mach-Zehnder modulation device followed by a filter, or a photonically driven device such as a stimulated Brillouin scatterer, a stimulated Raman scatterer, or a four-wave mixer. In certain embodiments, component cost can be reduced by selecting the modulation device 16 optimized for shifting within a specific frequency range.

Referring to Figure 2, the modulation device used in certain embodiments may be the quadrature Mach-Zehnder modulation device 16a. A quadrature device facilitates wavelength shifting by quadrature or single sideband modulation. The quadrature Mach-Zehnder modulation device 16a may have an upper branch 28 and a lower branch 30. The upper branch 28 and the lower branch 30 may be complementary Mach-Zehnder modulators that perform in a quadrature mode when driven by a modulation waveform 26.

With a quadrature modulation device, the modulation waveform 26 may have a quadrature waveform component 26a and a quadrature waveform component 26b. Waste light

31 may be emitted at a branch junction 32. In some embodiments it may be desirable to use the waste light from the branch junction 32 to perform phase stabilization or other useful functions.

Referring to Figure 3, a transfer function 34 typical of the upper branch 28 and the lower branch 30 may be a function of the voltage of the modulation waveform 26. The transfer function 34 may correspond to a cosine wave. In certain embodiments, the modulation synthesizer 12 may provide a waveform optimized to for a particular modulation device 16. Proper biasing of the upper branch 28 and the lower branch 30 modulation waveform voltages allow each branch to operate at a dark point 36. Operating at the dark point 36 may be advantageous to reduce transmitted power and signal distortion.

In certain embodiments, applying a ramp function beginning at the dark point 36 produces a sine wave of negative polarity. Therefore, small fluctuations in quadrature waveform components 26a and 26b about the dark point 36, produce modulations that are substantially bipolar and linear. Small fluctuations in the quadrature waveform components 26a and 26b that are not biased to the dark point 36 may produce modulations that may be unipolar. Transmitted power may also be substantially increased. Larger amplitude fluctuations in the modulation waveform 26 may generate noise harmonics in the channelized photonic signal 20 due to the non-linearities in the upper branch 28 and the lower branch 30.

Noise harmonics in the channelized photonic signal 20 may be substantially eliminated by dividing the modulation waveform components 26a and 26b by the transfer function 34 of the upper branch 28 and the lower branch 30. Driving the depicted Mach-Zehnder quadrature modulation device 16a with waveform components 26a and 26b, that are triangular or sawtooth in shape (having maximum and minimum amplitudes corresponding to peaks and valleys in the

transfer function 34), substantially eliminates the introduction of noise harmonics in the channelized photonic signal 20.

The modulation synthesizer 12 may be embodied in a variety of forms including discrete circuitry, digital logic, software modules within a processor (with a digital-analog converter to drive the modulation device), and custom chips. Regardless of the implementation scheme selected, the modulation synthesizer 12 may be designed to drive the modulation device 16 as controlled by the error signal 21 and the shift signal 24. Implementation details may be quite specific to the modulation device used and other factors such as bandwidth, cost, and response time.

In particular, the method of data keying and the characteristics of the modulation device 16 may significantly affect the overall structure of the modulation synthesizer 12. With certain embodiments it may be beneficial to embed data keying within the shift signal 24 (external to the modulation synthesizer 12). Figures 4, 5 and 7 show three examples of a modulation synthesizer 12 that share certain common design elements with unique changes relevant to the respective method of data keying and the characteristics of the modulation device 16 used by each example.

Referring to Figure 4 specifically, while referring generally to all the Figures, the modulation synthesizer 12 may include an integration unit 38. The integration unit integrates and may optionally filter the error signal 21 to provide an integrated error signal 40. For example, low-pass filtering of the error signal 21 may be used to dampen the response of the wavelength shifter 10 and prevent overshooting a design point. A summing unit 42 may sum the shift signal 24 with the integrated error signal 40 and provide a total shift signal 44. In some

embodiments, the shift signal 24 may provide a lower shift 24a and an upper shift 24b to restrict the range of wavelength shifting. The summing unit 42 may be configured to confine the total shift signal 44 to the range specified by the lower shift 24a and the upper shift 24b.

Continuing to refer to Figure 4 specifically, while referring generally to all the Figures, the waveform generator 46 receives a total shift signal 44 and generates the modulation waveform 26 relevant to the modulation device 16. Quadrature versions of the modulation device 16 may require a quadrature waveform with waveform components that are substantially 90 degrees out of phase.

Referring to Figure 5, a quadrature version of the modulation synthesizer 12 may configure the waveform generator 46 to generate quadrature waveform components 26a and 26b that are shaped in a desired fashion, such as triangle waves. Figure 5 also shows that ON/OFF data keying may be added to the modulation synthesizer 12 by operably connecting the data signal 22 to an ON/OFF input 47 of the waveform generator 46. Data keying may be accomplished by selectively setting the quadrature waveform components 26a and 26b to a value corresponding to the dark point 36 of the upper branch 28 and the lower branch 30. For example, the upper branch 28 and the lower branch 30 may be operably set at the dark point 36 when the ON/OFF input 47 is in the OFF position.

Referring to Figure 6, the phase modulation device 16b may differ from the quadrature Mach-Zehnder device 16a. For example, quadrature or single sideband modulation may not be supported. Wavelength shifting may occur by applying an alternative waveshape, such as a ramp function, to the input. In the illustrated embodiment, the extent of wavelength shifting provided

by the phase modulation device 16b may be substantially proportional to the slope of the ramp function.

Sustaining a ramp function may be problematic with a finite modulation waveform 26 and the phase modulation device 16b. Several techniques may be used to ensure that finite limits are maintained on the modulation waveform 26. For example, frequency shift keying may encode ones with a positive frequency shift and zeros with a negative frequency shift. Circuit modifications may be added to substantially eliminate the DC terms of the data signal. Data encoding techniques may be applied to limit the one's density of the data stream to an acceptable range. Each of these techniques may limit the range of wavelength shifting attainable by the wavelength shifter 10.

Another solution involves driving the phase modulation device 16b with a sawtooth waveform 26c. The sawtooth waveform 26c may produce an opposite polarity wavelength spike 27 corresponding to vertical edges of the sawtooth waveform 26c. The duration of the opposite polarity wavelength spike 27 may be short enough to be irrelevant. The opposite polarity wavelength spike 27 may also cause a wavelength shift large enough to momentarily move the wavelength of the channelized photonic signal 20 outside the transmission range of the system of interest. The opposite polarity wavelength spike 27 may also be advantageously used to provide a clock signal and/or synchronize multiple data streams.

Referring to Figure 7, the modulation synthesizer 12 may be configured to support frequency shift keying. As compared to the embodiments of Figures 4 and 5, a multiplexer has been added and the shift signal expanded to a low shift 24a and a high shift 24b. In the depicted embodiment, the low shift 24a and the high shift 24b are negative and positive shifts as depicted

(not necessarily of the same magnitude). The data signal 22 may multiplex between a low shift 24a and a high shift 24b to provide a data-keyed shift signal 48. A sawtooth waveform generator 46a may be a simple embodiment of a waveform generator 46 designed specifically to operate with the phase modulation device 16b. The modulation waveform 26 provided by the sawtooth waveform generator 46a may be restricted to a sawtooth wave. The sawtooth waveform generator 46 may integrate the total shift signal 44 until reset by a clock signal 49.

As mentioned previously, data keying may significantly affect the structure of the modulation synthesizer 16 specifically and the wavelength shifter 10 generally. In certain embodiments data keying may involve placing a separate phase modulation device 16b in series with the modulation device 16. Other embodiments may involve modifying the modulation device 16 to receive a data keying signal separate from the (wavelength shifting and stabilizing) modulation waveform 26. In many embodiments, however, information to control data keying, wavelength shifting, and wavelength stabilization may be embedded in the modulation waveform 26.

Referring to Figure 8 specifically, while referring generally to all the Figures, the wavelength error detector 14 may include a filter apparatus 50. In one embodiment the filter 50 may include a pair of matched filters 51a and 51b that are slightly offset in wavelength. The wavelength error detector 14 controls the stabilization performed by the wavelength shifter 10 and in certain embodiments may dramatically influence the effectiveness of the wavelength shifter 10.

A differential detector 52 may detect differences of intensity in the output of filter devices 51a and 51b. Figure 8 depicts a pair of filter devices 51a and 51b, which may be fixed. Fixed

filter devices may be sufficient in some applications and may be Bragg filters. In some embodiments, tunable Bragg filters with slightly offset tuning inputs may increase the variety of wavelength patterns supportable with the wavelength error detector 14.

Referring to Figure 9, a tunable version of the wavelength error detector 14 may be comprised of a complementary pair of modulation devices 16a and 16b configured to wavelength shift the channelized photonic signal 20 as directed by the modulation synthesizer 12. In one embodiment, the shift signal 24 carries a wavelength pattern corresponding to a wavelength pattern present on the channelized photonic signal 20.

A complementary pair of modulation devices 16a and 16b may be driven to wavelength shift by a common value corresponding to a wavelength pattern carried by the shift signal 24. Additionally, a slight wavelength offset may be produced between a shifted photonic signal 54a and a shifted photonic signal 54b. Wavelength shifting the channelized photonic signal 20 by slightly different amounts allows the use of a single filter device 51 in the filter apparatus 50 instead of the pair of matching filters devices 51a and 51b slightly offset in wavelength. Filter 51 may be a standard Bragg filter.

Referring to Figure 10, another tunable version of the wavelength error detector 14 may include a filter apparatus 50 having a complementary pair of circulators 55a and 55b, and a bidirectional filter 51c. The bidirectional filter 51c may be a standard Bragg filter. The complementary pair of circulators 55a, 55b may direct the shifted photonic signal 54a and the shifted photonic signal 54b to opposite ends of the bidirectional filter device 51c. The complementary pair of circulators 55a and 55b may also direct the reflected portion of the shifted

photonic signal 54a and the reflected portion of the shifted photonic signal 54b to the differential detector 52.

The tunable versions of the wavelength error detector 14 depicted in Figures 9 and 10 may be designed to create a time-varying wavelength reference using a standard fixed filter device such as a Bragg filter. For example, the channelized photonic signal 20 received by the wavelength error detector 14 may have a wavelength pattern characterized by a spreading function. The complementary pair of modulation devices 16a, 16b may be driven by a modulation waveform characterized by a gathering function corresponding to the spreading function of the channelized photonic signal 20. By using a gathering function that essentially “unspreads” the spreading function, the shifted photonic signals 54a, 54b may be substantially fixed in wavelength. Having substantially fixed wavelengths for the shifted photonic signals 54a, 54b may facilitate using a standard fixed filter device such as a Bragg filter in the wavelength error detector 10.

Some wavelength variability between filter devices may be expected. Additionally, filter device wavelengths are often temperature sensitive. In certain embodiments, temperature- and device-dependent variations between standard filter devices 51 may be compensated. One method of compensation is further adjusting the value of the shift signal 24 of the modulation synthesizer 12 to account for temperature- and device-dependent variations. Thus a modulation synthesizer 12 becomes a temperature-dependent-device-compensation mechanism. A temperature-dependent- device-compensation shift may be stored and accessed externally or internally to the modulation synthesizer 12.

In some embodiments, a tunable version of the wavelength error detector may be shared among multiple wavelength shifters 10. For example, the channelized photonic signals 20 from multiple wavelength shifters 10 may be combined onto a single fiber. On that fiber, a single wavelength error detector 14 may be configured to time-division multiplex between the various channels and provide a time-division-multiplexed wavelength error signal. Additionally, the modulation synthesizer 12 may be configured to sample and hold the wavelength error signal 21 at an appropriate time.

The wavelength shifter 10 provides a convenient building block for creating photonic systems including transmission, switching and multiplexing equipment. Photonic data streams and/or photonic carriers arriving in a photonic signal 18 may be shifted, stabilized and channelized to become the channelized photonic signal 20. This may be done without conversion to the electronic domain. Photonic data rates and throughput may be maintained, while complex control features may be handled in the electronic domain.

Another feature of the wavelength shifter 10 is the ability to transparently pass the photonic signal 18 without knowledge of the encoding techniques or format used to create the photonic signal 18. The transparent nature of the wavelength shifter 10 and the ability to channelize photonic signals facilitates the transmission, multiplexing and switching of an extremely wide range of photonic signals.

The wavelength shifter 10 may also compensate for wavelength variability of existing photonic streams without retransmission. Data may be pre-encoded into the photonic signal 18, or data may be encoded onto the channelized photonic signal 20. Encoding may occur via the shift signal 24 or the optional data signal 22.

Referring to Figure 11, a channel allocation mechanism may automatically channelize and transparently transmit data-encoded photonic streams across a network of photonic equipment without prior knowledge of the carrier wavelengths and data encoding techniques. A channel shifter 58 may have a wavelength detector 60 to receive the photonic signal 18, or the channelized photonic signal 20, and provide a wavelength signature 62.

In certain embodiments, the wavelength signature 62 captures the essential wavelength characteristics of each carrier in a composite or non-composite photonic signal. The channel shifter 58 may also include a wavelength shifter 10 configured to receive the photonic signal 18, or the channelized photonic signal 20, as an input and provide the channelized photonic signal 20 as an output. A channel allocator 64 may be configured to receive the wavelength signature 62 and provide a shift signal 24 that directs the photonic signal 18 or the channelized photonic signal 20 into an available channel.

In some embodiments, the channel allocator 64 may be shared by all the channel shifters 58 common to a system. Sharing the channel allocator 64 simplifies resource allocation, relieves contention and resolves update and data synchronization issues. Multiple channel allocators 64 may also coordinate and update through a variety of methods.

One distributed solution involves assigning a local pool of identified channels to each channel allocator. When a channel allocator exhausts the local pool of channels, a message may be sent to other channel allocators requesting borrowing of a channel from their pool. The request may be accommodated, brokered, negotiated, denied or the like. Regardless of the method relied upon, the channel allocator 64 provides a shift signal to the channel shifter 58. The shift

signal shifts the photonic signal 18 or the channelized photonic signal 20 into an available channel.

Referring to Figure 12, a tunable photonic transmitter 70 may include a coherent light source 72 and a wavelength shifter 10. The photonic signal 18 provided by the coherent light source 72 may have a limited coherence length. The photonic signal 18 may have wavelength jitter sufficient to be unacceptable for a particular application. Additionally, the wavelength of the photonic signal 18 may be offset from the desired wavelength.

The tunable photonic transmitter 70 may shift and stabilize the photonic signal 18 via the wavelength shifter 10 and provide the channelized photonic signal 20. The tunable photonic transmitter 70 may also encode the data signal 22 into the channelized photonic signal 20. The channelized photonic signal 20 may be a spread spectrum channel.

An ability to encode, shift and stabilize the photonic signal 18 independent of the coherent light source 72 may provide additional benefits over standard photonic transmitting circuits. The coherent light source 72 need not be tunable, stable or precise. The coherent light source 72 may be physically and electronically separated from the rest of the photonic transmitter 70. A single optical fiber may connect the coherent light source 72 with the wavelength shifter 10. Performance specifications of the channelized photonic signal 20 may be determined primarily by the electronic circuitry of wavelength shifter 10 rather than the photonics of the coherent light source 72.

Referring to Figure 13, a recursive wavelength shifter 74 may include a shifting loop 76 and an output filter 78. The shifting loop 76 may receive the photonic signal 18, having one or more wavelengths, and provide a photonic signal 18 with a spectral pattern 80. The spectral

pattern 80 may have increasing or diminishing spectral tilt. The spacing and number of wavelengths of the spectral pattern 80 may be varied by the shift signal 24.

The shifting loop 76 may include an amplifier 82, a loop filter 84, and the wavelength shifter 10. The gain of the amplifier 82 may compensate for losses in the shifting loop 76 and contribute to the amount of spectral tilt in the spectral pattern 80. The loop filter 84 may shape the spectral pattern 80 with an arbitrary spectral envelope.

Referring to Figure 14 while also referring to Figure 13, some embodiments the shifting loop 76 effectively generate a spectral comb 86. The spacing of the “teeth” of the spectral comb 86 may be controlled by the shift signal 24. In other embodiments the spectral pattern 80 may be repeating and continuous instead of having discrete “teeth.” The shape of the repeating portion of the spectral pattern 80 may be provided by the photonic signal 18.

The output filter 78 may receive a photonic signal with the spectral pattern 80 and provide a spectrally shaped photonic signal 87. As shown in Figure 14, the output filter 78 may select one tooth or region from the spectral pattern 80 and substantially suppress other teeth or regions of the spectral pattern 80. The recursive wavelength shifter 74 may include multiple output filters 78. Each output filter 78 may select a different tooth or region and provide a unique spectrally shaped photonic signal 87.

From the above discussion, it will be appreciated that the present invention may be embodied in other specific forms without departing from its spirit or essential characteristics. The described embodiments are to be considered in all respects only as illustrative, and not restrictive. The scope of the invention is, therefore, indicated by the appended claims, rather

than by the foregoing description. All changes which come within the meaning and range of equivalency of the claims are to be embraced within their scope.

What is claimed and desired to be secured by United States Letters Patent is:

10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225